



**WOYR2.E98133**  
**Switches, Appliance and Special Use - Component**

For enhanced search functionality, please visit UL's [iQ™ Family of Databases](#).  
 Click on a product designation for complete information.

[Page Bottom](#)

**Switches, Appliance and Special Use - Component**

[See General Information for Switches, Appliance and Special Use - Component](#)

**EVEREL GROUP SPA**  
 VIA CAVOUR 9  
 37067 VALEGGIO SUL MINCIO, VR ITALY

E98133

Investigated to ANSI/UL 1054

Cat. No.	Amps	Volts	Hz	Load	Endurance	Temp C	POL/THR	Per Pole/Circuit Code	SPCOA
<b>04-0044.0175</b>									
	2	24	DC	-	6K	105	1/1	-/-	8
<b>04-0044.0190</b>									
	16	250	50	GP	20K	105	1/1	-/-	Note A1, A2
<b>04-0044.0191</b>									
	6	250	50	GP	20K	105	2/1	PP/-	Note A2
<b>04-0044.0192</b>									
	-	-	-	GP	-	105	-	-/-	Note A2
<b>04-0076 w suffix 0010, 0001 or 0002</b>									
	0.25	250	60	GP	6K	70	1/1	-/-	Note 5
<b>04-0076 w suffix 0011 or 0014 thru 0018</b>									
	0.1	250	60	GP	6K	105	1/1	-/-	Note 6
<b>1-DP w suff</b>									
	4	250	60	GP	6K	70	M/1	-/-	-
	16	250	60	R	6K				
<b>1-DPS/232,1-DPS/235,1-DPS/226, 1-DPS/228</b>									
	12	125	60	GP	10K	85	1/M	-/-	-
<b>1-DX f/b 2 or 3 digits</b>									
	13	250	60	GP	6K	80	2/1	PP/-	-
<b>1-DY or 2-DY Series w suffix f/b 2 or 3 digits</b>									
	13	250	60	GP	6K	80	M/M	PP/-	1
	14	250	60	GP	6K				
<b>1Wi-XII/761</b>									
	4	250	60	TV	25K	65	2/1	PP/-	-
<b>1Wi36, 1Wi36A</b>									
	10	250	60	GP	6K	65	M/1	PP/-	2
<b>1Wi36, 2Wi36</b>									
	16	250	60	GP	6K	65	M/1	PP/-	2
<b>1WiXII-761</b>									
	10	250	60	GP	6K	65	M/M	PP/-	Note 7, 8
<b>2-DLF w/wo suffixes</b>									
	10	250	60	GP	6K	85	M/1	-/-	2
	1	250	60	GP	6K				

<b>2H-7H (ad)</b>	4	250	60	GP	6K	150	M/M	PP/-	Note 4
	16	250	60	R	6K				
	2	277	60	GP	6K				
	10	277	60	R	6K				
<b>2Wi 32 w suff</b>									
	12	250	60	GP	6K	65	2/M	-/-	2
<b>2Wi36, 2Wi36B</b>									
	16	125	60	GP	6K	65	M/2	PP/-	2
<b>2Wi38</b>	16	250	60	GP	6K	65	2/1	-/-	2, 3
	-	250	60	1/2hp	6K				
<b>81 w prefix SX f/b 2 digits f/b 1, 3, 4, 5, 6, A, B f/b 8 f/b 8 digits</b>									
	16	250	50/60	GP	6K	105	1/M	PP/-	3, A1, A2
	-	250	50/60	3/4hp	6K				
	20	125	50/60	GP	6K				
	-	125	50/60	3/4hp	6K				
<b>81 w prefix SX f/b 2 digits f/b 6 f/b B f/b 8 digits</b>									
	16	250	50/60	GP	6K	105	1/1	-/-	3, A1, A2
	-	250	50/60	3/4hp	6K				
<b>81 w prefix SX f/b 2 digits f/b 6 f/b C f/b 8 digits</b>									
	20	125	50/60	GP	6K	105	1/1	-/-	3, A1, A2
	-	125	50/60	3/4hp	6K				
<b>82 w prefix SX f/b 2 digits f/b 1, 2, 3, 4, 7, 8, L, M, T, V, P, W f/b 8 or X f/b 8 digits</b>									
	16	250	50/60	GP	6K	105	M/M	PP/-	3, A1, A2
	-	250	50/60	3/4hp	6K				
	20	125	50/60	GP	6K				
	-	125	50/60	3/4hp	6K				
<b>82 w prefix SX f/b 2 digits f/b 3, 6, 8, P, T, V, W f/b B f/b 8 digits</b>									
	16	250	50/60	GP	6K	105	M/M	PP/-	3, A1, A2
	-	250	50/60	3/4hp	6K				
<b>82 w prefix SX f/b 2 digits f/b 5, 9 f/b 8 f/b 8 digits</b>									
	16	250	50/60	GP	6K	105	M/M	PP/-	3, A1, A2
	-	250	50/60	3/4hp	6K				
	16	125	50/60	GP	6K				
	-	125	50/60	3/4hp	6K				
<b>82 w prefix SX f/b 2 digits f/b 8, T, W f/b C f/b 8 digits</b>									
	20	125	50/60	GP	6K	105	M/M	PP/-	3, A1, A2
	-	125	50/60	3/4hp	6K				
<b>82 w prefix SX f/b 2 digits f/b E f/b 8 f/b 8 digits</b>									
	12	250	50/60	GP	6K	105	M/M	PP/-	3, A1, A2
	-	250	50/60	1/4hp	6K				
	15	125	50/60	GP	6K				
	-	125	50/60	1/4hp	6K				
<b>83 w prefix SX f/b 1 digit f/b 1, 3, 4, 6, B, D, E, F, G, W f/b 8 or X f/b 9 digits</b>									
	16	250	50/60	GP	6K	105	M/M	PP/-	3, A1, A2
	-	250	50/60	3/4hp	6K				
	20	125	50/60	GP	6K				
	-	125	50/60	3/4hp	6K				



	0.1	250	60	GP	6K				
	-	125	60	3/4hp	6K				
<b>CK f/b one digit, f/b 1, f/b 2, f/b six digit, may be f/b W.</b>									
	16	125	50/60	GP	6K	65	2/1	PP/C	-
<b>CS f/b one digit, f/b 1, f/b 2, f/b six digit, may be f/b W.</b>									
	16	125	50/60	GP	6K	65	2/1	PP/C	-
<b>D1</b>	16	125	60	1hp	6K	105	1/1	-/-	2
	16	250	60	1hp	6K				
	12	125	60	GP	6K				
	12	250	60	GP	6K				
<b>D1 Momentary</b>									
	12	125	60	1/2hp	6K	105	1/1	-/-	2
	12	250	60	1/2hp	6K				
	12	125	60	GP	6K				
	12	250	60	GP	6K				
<b>DC</b>	16	125	60	GP	6K	65	1/2	-/-	-
	8	250	60	GP	6K				
<b>DG w pref 3-9 w suffixes</b>									
	16	250	60	GP	6K	85	M/M	PP/-	3
	0.5	250	60	GP	6K				
	2	250	60	GP	6K				
<b>DH, f/b 2, 3 or 4, f/b two digits, may be followed by W</b>									
	2	125	50/60	GP	6K	85	1/M	-/A	-
<b>DM</b>	16	125	60	GP	6K	65	M/1	PP/-	-
	8	250	60	GP	6K				
<b>DPS w Pref 1-10 w/wo suffixes w PCB contacts w cross contacts w Low Voltage contacts (d)</b>									
	16	250	60	GP	6K	65	1/M	PP/-	2, 3, 5, Note 2, 3
	-	125	60	3/4hp	6K				
	4.4	125	60	GP	6K				
	-	125	60	1/6hp	6K				
	6	250	60	GP	6K				
	0.5	6	DC	-	6K				
	0.1	24	60	GP	6K				
<b>DQ, DK</b>	16	125	60	GP	6K	105	2/2	-/-	-
	8	250	60	GP	6K				
<b>DS, f/b 1-999, f/b suffix.</b>									
	2	250	50/60	GP	6K	65	1/M	-/A	-
<b>DV</b>	16	125	60	GP	6K	65	2/1	PP/-	-
	8	250	60	GP	6K				
<b>DY-T125 or DY-T12 Series</b>									
	14	250	60	GP	6K	125	M/M	-/-	-
<b>DY1, DY2 f/b 5 digit, f/b C or K or H, f/b 3 digit</b>									
	13	250	50/60	GP	6K	80	M/M	-/-	1
	14	250	50/60	GP	6K				
	-	125	50/60	1/3hp	6K				
	-	250	50/60	3/4hp	6K				
<b>DY1, DY2 f/b 5 digit, f/b D or L or M, f/b 3 digit</b>									





<b>L5, f/b 1-8, f/b 3, f/b A-G, K-N, f/b 73, w/suffixes</b>									
	6	125	60	GP	6K	150	M/5	PP/-	3
	4	250	60	GP	6K				
<b>L5, f/b 1-8, f/b 4, f/b A-G, f/b 73, w/suffixes</b>									
	6	125	60	GP	6K	150	M/5	PP/-	3
	4	250	60	GP	6K				
<b>LITE f/b 1, f/b 1, A, 2, B, 3, C, 5, E, 7 or 8, f/b A, f/b 1, 4, 2, 7, 5, N, 8, R, 6 or S, f/b C or H</b>									
	16	125	60	GP	6K	100	M/1	-/-	3, 7
	16	250	60	GP	6K				
	-	125	60	1/2hp	6K				
	-	250	60	3/4hp	6K				
<b>LITE 1AA5CLG001, LITE 1AA5HLG001</b>									
	16	250	50/60	GP	6K	100	1/2	-/-	3, 7
	0.5	250	50/60	GP	6K				
<b>LR w/suffixes</b>									
	12	125-250	60	GP	6K	100	M/M	-/-	1, 2
	-	125	60	1/4hp	6K				
	-	250	60	1/2hp	6K				
<b>MP4</b>	10	125	50/60	GP	6K	85	1/M	-/A	-
	5	250	50/60	GP	6K				
<b>P1 f/b 2, f/b 4, 7, N, P, R, S, T or V, f/b 3</b>									
	2	125	50/60	GP	6K	65	M/1	PP/D1	2
<b>P2L, P2LC, P3L, P3LC, P4L, P4LC, P5L, P5LC</b>									
	13	125	60	GP	6K	65	M/M	-/-	-
	6.5	250	60	GP	6K				
	-	125	60	1/4hp	6K				
<b>QFIT f/b 1, 2 or 3, f/b 1, A, 2, B, 3, C, 5, E, 7 or 8, f/b 1, 4, 2, 7, 5, N, 8, R, 6 or S, f/b C</b>									
	16	125	50/60	GP	6K	65	M/1	-/-	3, 7
	16	250	50/60	GP	6K				
	-	125	50/60	1/2hp	6K				
	-	250	50/60	3/4hp	6K				
<b>QFIT f/b 1, 2 or 3, f/b 1, A, 2, B, 3, C, 5, E, 7 or 8, f/b 1, 4, 2, 7, 5, N, 8, R, 6 or S, f/b H</b>									
	16	125	50/60	GP	6K	100	M/1	-/-	3, 7
	16	250	50/60	GP	6K				
	-	125	50/60	1/2hp	6K				
	-	250	50/60	3/4hp	6K				
<b>R-FIT f/b 1, f/b 2 or 8, f/b 1, 4, 2, 7, 5, N, 6, S, 8 or R, f/b C</b>									
	16	125	50/60	GP	6K	65	M/1	-/-	3, 7
	16	250	50/60	GP	6K				
	-	125	50/60	1/2hp	6K				
	-	250	50/60	3/4hp	6K				
<b>R-FIT f/b 1, f/b 2 or 8, f/b 1, 4, 2, 7, 5, N, 6, S, 8 or R, f/b H</b>									
	16	125	50/60	GP	6K	100	M/1	-/-	3, 7
	16	250	50/60	GP	6K				
	-	125	50/60	1/2hp	6K				
	-	250	50/60	3/4hp	6K				
<b>R-MASK f/b 1, f/b 2 or 8, f/b 1, 4, 2, 7, 5, N, 6, S, 8 or R, f/b C</b>									

	16	125	50/60	GP	6K	65	M/1	-/-	3,7,A1
	16	250	50/60	GP	6K				
	-	125	50/60	1/2hp	6K				
	-	250	50/60	3/4hp	-				
<b>R-MASKf/b 1, f/b 2 or 8, f/b 1, 4, 2, 7, 5, N, 6, S, 8 or R, f/b H</b>									
	16	125	50/60	GP	6K	100	M/1	-/-	3,7,A1
	16	250	50/60	GP	6K				
	-	125	50/60	1/2hp	6K				
	-	250	50/60	3/4hp	-				
<b>R-XXXX1XXX ww/o W, R-XXXX3XXX ww/o W, where X is any number or letter</b>									
	13	125	60	GP	6K	65	2/2	-/-	-
<b>R-XXXX2XXX, where X is any number or letter</b>									
	10	125	60	GP	6K	120	2/2	-/-	-
	15	125	60	GP	6K				
<b>Rating Code 4</b>									
	10	125	60	GP	-	-	-	-/-	-
	10	250	60	GP	-				
	-	125	60	1/3hp	-				
	-	250	60	1/2hp	-				
<b>Rating Code B</b>									
	10	125	60	GP	-	-	-	-/-	-
	10	250	60	GP	-				
<b>Rating Code C or E</b>									
	20	125	60	GP	-	-	-	-/-	-
	16	250	60	GP	-				
	-	125	60	1/3hp	-				
	-	250	60	3/4hp	-				
<b>Rating Code D</b>									
	20	125	60	GP	-	-	-	-/-	-
	-	125	60	1/3hp	-				
<b>SCM12</b>	13	125	60	GP	6K	65	2/2	PP/-	3
	-	125	60	3/4hp	6K				
<b>Series 7404, 7574.2, 7564.2</b>									
	10	125	60	GP	6K	65	1/3	-/-	3
	5	250	60	GP	6K				
	-	125	60	1/4hp	6K				
	-	250	60	1/4hp	6K				
<b>Series 83, 84, 88</b>									
	13	125-250	60	GP	6K	95	1/M	-/-	2, 3
<b>Series 9661, Type 949 f/b 0 through 7, f/b 0 through 9, f/b 20 through 36, f/b 3 digits.</b>									
	20	125	60	GP	6K	65	M/M	-/-	9
	10	250	60	GP	6K				
<b>Series A1, A2, A4 f/b suffix letter or number f/b suffix letter or number f/b rating code 2 w/wo suffixes*</b>									
	6	125-250	50/60	GP	6K	105	M/1	PP/A, D1	2, Note 1
	-	125	50/60	1/10hp	6K				
	-	250	50/60	1/6hp	6K				
<b>Series A1, A2, A4 f/b suffix letter or number f/b suffix letter or number f/b rating code 3 w/wo suffixes*</b>									



	10	125-250	50/60	GP	6K	105	M/1	PP/A, D1	2, Note 1
	-	125	50/60	1/3hp	6K				
	-	250	50/60	1/2hp	6K				
<b>Series A1, A2, A4 f/b suffix letter or number f/b suffix letter or number f/b rating code 6 w/wo suffixes*</b>									
	6	125-250	50/60	GP	6K	105	M/1	PP/A, D1	2, Note 1
	-	125	50/60	1/8hp	6K				
	-	250	50/60	1/6hp	6K				
<b>Series A1, A2, A4 f/b suffix letter or number f/b suffix letter or number f/b rating code 7 w/wo suffixes*</b>									
	10	125-250	50/60	GP	6K	105	M/1	PP/A, D1	2, Note 1
	-	125	50/60	1/10hp	6K				
	-	250	50/60	1/6hp	6K				
<b>Series A1, A2, A4 f/b suffix letter or number f/b suffix letter or number f/b rating code B w/wo suffixes*</b>									
	15	125	50/60	GP	6K	105	M/1	PP/A, D1	2, Note 1
	10	250	50/60	GP	6K				
	-	125	50/60	1/3hp	6K				
	-	250	50/60	1/2hp	6K				
<b>Series A4 and A3 w/suffix T105* and additional suffixes</b>									
	16	125	60	3/4hp	6K	105	M/M	-/-	-
	16	250	60	3/4hp	6K				
	16	125	60	1/3hp	6K				
	16	250	60	1/2hp	6K				
<b>Series A4 and A3 w/suffix T65* and additional suffixes</b>									
	16	125	60	3/4hp	6K	105	M/M	-/-	-
	16	250	60	3/4hp	6K				
	16	125	60	1/3hp	6K				
	16	250	60	1/2hp	6K				
<b>Series A8 f/b suffix letter or number, f/b 2 or 8, f/b rating code 2 w/wo suffixes</b>									
	6	125-250	60	GP	6K	65	2/1	PP/D1	2, Note 1
	-	125	60	1/10hp	6K				
	-	250	60	1/6hp	6K				
<b>Series A8 f/b suffix letter or number, f/b 2 or 8, f/b rating code 3 w/wo suffixes</b>									
	10	125-250	50/60	GP	6K	65	2/1	PP/D1	2, Note 1
	-	125	50/60	1/3hp	6K				
	-	250	50/60	1/2hp	6K				
<b>Series B1 f/b letter or number f/b letter or number f/b rating code 4 w/wo suffixes</b>									
	16	125	60	GP	6K	105	1/M	-/-	2, 3, 10
	10	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/2hp	6K				
<b>Series B1 f/b letter or number f/b letter or number f/b rating code B w/wo suffixes</b>									
	10	125	60	GP	6K	105	1/M	-/-	2, 3, 10
	10	250	60	GP	6K				
<b>Series B1 f/b letter or number f/b letter or number f/b rating code C, E w/wo suffixes</b>									
	20	125	60	GP	6K	105	1/M	-/-	2, 3, 10, Note 1
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	3/4hp	6K				





Series B4MASK f/b terminal code, f/b function code, f/b Rating Code C, E, R w/wo suffixes									
	20	125	60	GP	6K	105	M/M	PP/-	3, 9, 10, 11, Note 1
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	3/4hp	6K				
	-	125	60	3/4hp	6K				
Series B4MASK f/b terminal code, f/b function code, f/b Rating Code N w/wo suffixes									
	20	125	60	GP	6K	105	M/M	PP/-	3, 9, 10, 11, Note 1
	16	250	60	GP	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
Series B4MASK f/b terminal code, f/b function code, f/b Rating Code S w/wo suffixes									
	25	125	50/60	GP	6K	105	M/M	PP/-	3, 9, 10, 11
	16	250	50/60	GP	6K				
	-	125	50/60	3/4hp	6K				
	-	250	50/60	3/4hp	6K				
Series CATENARIA SQR f/b suffix letter, f/b suffix numbers									
	0.2	250	60	GP	6K	120	1/1	-/-	-
Series E2, E3, E4 f/b 1-4 or A-D f/b 1-9 or A-Z Above Series E3 with 5th character "G"									
	16	125-250	60	GP	6K	65	M/M	PP/-	-
	-	125	60	1/3hp	6K				
	-	250	60	3/4hp	6K				
	13	125-250	60	GP	6K				
Series HE, f/b 11-50 w/prefix 3 to 19, f/b U									
	16	250	60	GP	6K	120	2/M	PP/-	-
Series HP									
	13	125	60	GP	6K	120	M/M	-/-	-
Series J5									
	16	125	60	3/4hp	6K	100	M/1	-/-	1
	16	250	60	3/4hp	6K				
Series LF may be f/b 2, 3 or 4									
	8	125	60	GP	6K	65	M/M	PP/-	2, 3
Series MD									
	10	125	60	GP	6K	105	1/1	-/-	7
	5	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
Series SCA: 058, f/b 4 or 5, f/b 0-4, f/b Rating Code 2, f/b suffix.									
	2	125-250	60	GP	6K	65	1/1	-/-	3, Note 2
	-	-	-	GP	-				
	-	-	-	GP	-				
Series SCA: 058, f/b 4 or 5, f/b 0-4, f/b Rating Code 4 or 6, f/b suffix.									
	6	125-250	60	GP	6K	65	1/1	-/-	3, Note 2
	-	125	60	1/8hp	6K				
	-	250	60	1/6hp	6K				
Series SCL L2, f/b 1-4, f/b 3, f/b A-G, K, L, f/b 73, w/suffixes									
	6	125	60	GP	6K	150	M/2	PP/-	3
	4	250	60	GP	6K				
Series SCL L2, f/b 1-4, f/b 4, f/b A-G, f/b 73, w/suffixes									

	6	125	60	GP	6K	150	M/2	PP/-	3
	4	250	60	GP	6K				
<b>Series SCL L3, f/b 1-8, f/b 3, f/b A-H, K,L,M, f/b 73, w/suffixes</b>									
	6	125	60	GP	6K	150	M/3	PP/-	3
	4	250	60	GP	6K				
<b>Series SCL L3, f/b 1-8, f/b 4, f/b A-H, f/b 73, w/suffixes</b>									
	6	125	60	GP	6K	150	M/3	PP/-	3
	4	250	60	GP	6K				
<b>Series SCL L4, f/b 1-8, f/b 3, f/b A-H,K,L, M, N, f/b 73, w/suffixes</b>									
	6	125	60	GP	6K	150	M/4	PP/-	3
	4	250	60	GP	6K				
<b>Series SCL L4, f/b 1-8, f/b 4, f/b A-H,N, f/b 73, w/suffixes</b>									
	6	125	60	GP	6K	150	M/4	PP/-	3
	4	250	60	GP	6K				
<b>Series SCL L5, f/b 1-8, f/b 3, f/b A-G, K-N, f/b 73, w/suffixes</b>									
	6	125	60	GP	6K	150	M/5	PP/-	3
	4	250	60	GP	6K				
<b>Series SCL L5, f/b 1-8, f/b 4, f/b A-G, f/b 73, w/suffixes</b>									
	6	125	60	GP	6K	150	M/5	PP/-	3
	4	250	60	GP	6K				
<b>Series SCM-11</b>									
	15	125	60	GP	6K	95	M/1	-/-	3
<b>Series SCM7</b>									
	12	125	60	GP	6K	65	1/1	-/-	-
	6	250	60	GP	6K				
	-	125	60	1/4hp	6K				
	-	250	60	1/4hp	6K				
<b>Series SP, may be f/b L, f/b 63, f/b 1 or A, f/b 1, 2, 4, 5, 6, 7, 8, A, B, C, D, E, F, G, H, J, L, M, N, P, R, U, W or Z, f/b 7, f/b six digits.</b>									
	16	125-250	60	GP	6K	95	M/M	PP/-	2, 3
	-	125	60	1/4hp	6K				
	-	250	60	1/2hp	6K				
<b>Series SP, may be f/b L, f/b 60, f/b 1, 2, 3, 4, 5 or 6 or A, B, C, D, E or F, f/b 1, 2, 4 or 7, f/b 7, f/b six digits, f/b W.</b>									
	16	125-250	50/60	GP	6K	65	M/1	PP/A, D1	3
	-	250	50/60	1/2hp	6K				
	-	125	50/60	1/4hp	6K				
<b>Series SP, may be f/b L, f/b 60, f/b 1, 2, 3, 4, 5 or 6 or A, B, C, D, E or F, f/b 1, 2, 4 or 7, f/b 7, f/b six digits.</b>									
	16	125-250	50/60	GP	6K	95	M/1	PP/A, D1	3
	-	250	50/60	1/2hp	6K				
	-	125	50/60	1/4hp	6K				
<b>Series SP, may be f/b L, f/b 60, f/b 1, 2, 3, 4, 5 or 6 or A, B, C, D, E or F, f/b 5, 6, 8, N, P or R, f/b 7, f/b six digits w/wo W as suffix.</b>									
	16	125-250	60	GP	6K	95	1/M	PP/-	2, 3
	-	125	60	1/4hp	6K				
	-	250	60	1/2hp	6K				
<b>Series SPM, f/b 1, 2, 3, or 4, f/b A-Z, f/b 1-4, 7, 8, A-H, K-N, P, R-V or W, f/b C, w/wo additional suffixes.</b>									
	20	125	50/60	GP	6K	100	2/M	PP/-	-
	16	250	50/60	GP	6K				
	-	125	50/60	1/3hp	6K				



	16	250	60	GP	6K				
	-	125	60	1/2hp	6K				
	-	250	60	3/4hp	6K				
<b>UP f/b 1 or 2, f/b 1, A, 2, B, 3, C, 5, E, 7 or 8, f/b A, B, C or D, f/b 1, 2, 4 or 7, f/b H</b>									
	16	125	60	GP	6K	100	M/1	-/-	3, 7
	16	250	60	GP	6K				
	-	125	60	1/2hp	6K				
	-	250	60	3/4hp	6K				
<b>V5 w/suffixes</b>									
	10	125	60	GP	6K	75	1/M	-/-	2, 3
	10	250	60	GP	6K				
<b>V7 w/suffixes T60* and additional suffixes</b>									
	10	125	60	GP	6K	60	1/2	-/-	2
	10	250	60	GP	6K				
	-	125	60	1/10hp	6K				
	-	250	60	1/4hp	6K				
<b>V7 w/suffixes T65* and additional suffixes</b>									
	10	125	60	GP	6K	65	1/2	-/-	2
	10	250	60	GP	6K				
	-	125	60	1/10hp	6K				
	-	250	60	1/4hp	6K				
<b>V8 w/suffixes</b>									
	10	125-250	60	R	6K	65	M/M	PP/-	3
	4	250	60	GP	6K				
<b>Wi 23</b>	16	125-250	60	GP	6K	65	2/1	PP/-	2
<b>Wi 26</b>	16	125-250	60	GP	6K	65	2/1	PP/-	2
<b>Wi 32 w suff</b>									
	10	250	60	GP	6K	65	1/M	-/-	-
	16	125	60	GP	6K				
	8	277	60	GP	6K				
	12	125-250	60	GP	6K				
<b>Wi-XIX (ab)</b>	16	250	60	R	6K	65	1/M	-/-	2, 3
<b>Wi-XIX f/b -25 (ab)</b>									
	25	125	60	GP	6K	65	1/M	-/-	2, 3
<b>Wi-XV (ab)</b>	16	250	60	R	6K	65	1/M	-/-	3
<b>Wi-XV f/b -25 (ab)</b>									
	25	125	60	GP	6K	65	1/M	-/-	3
<b>Wi34</b>	16	125	60	GP	6K	65	M/M	PP/-	-
	12	250	60	GP	6K				
<b>Wi37</b>	16	250	60	GP	6K	65	M/M	PP/-	-
<b>WiXII (ab)</b>	16	250	60	GP	6K	65	M/M	PP/-	Note 7, 8
	-	250	60	3/4hp	6K				
	7	125	60	L	6K				
	25	250	60	GP	6K				
	22	24	DC	-	6K				
<b>WiXVI (ab)</b>	16	250	60	GP	6K	65	M/M	-/-	Note 7, 8
<b>WK f/b 2, 5, 16, 25, 30, 32, 34, 35, 36 or 37 w/wo R</b>									





	10	250	60	GP	6K				
<b>WNO f/b 1, 2, 3, 4, 5 or 6, f/b 2, f/b 1, 3 or 4, optional suffix</b>									
	6	125	60	GP	6K	80	M/M	-/-	-
	4	250	60	GP	6K				
<b>WNO f/b 1, 2, 3, 4, 5 or 6, f/b 3, f/b 1, 3 or 4 optional suffix</b>									
	10	125	60	GP	6K	80	M/M	-/-	-
	6	250	60	GP	6K				
<b>WNT f/b 1, 2, 3, 4, 5 or 6, f/b 2, f/b 1, 3 or 4, optional suffix</b>									
	6	125	60	GP	6K	80	M/M	-/-	-
	4	250	60	GP	6K				
<b>WZ f/b 1 thru 4, f/b 2, f/b 1, 2 or 3, optional suffix</b>									
	6	125	60	GP	6K	55	M/M	-/-	-
	4	250	60	GP	6K				
<b>WZ f/b 1 thru 4, f/b 3, f/b 1, 2 or 3, optional suffix</b>									
	10	125	60	GP	6K	55	M/M	-/-	-
	6	250	60	GP	6K				
<b>WZ f/b 5 thru 8, f/b 2, f/b 1, 2 or 3, optional suffix</b>									
	6	125	60	GP	6K	55	M/M	-/-	2
	4	250	60	GP	6K				
<b>WZ f/b 5 thru 8, f/b 3, f/b 1, 2 or 3, optional suffix</b>									
	10	125	60	GP	6K	55	M/M	-/-	2
	6	250	60	GP	6K				
<b>ZP</b>	12	125	60	GP	6K	65	1/M	-/-	2, 3
	12	250	60	GP	6K				
	-	125-250	60	1/4hp	6K				
<b>ZP w suffix T105**</b>									
	12	125	60	GP	6K	100	1/M	-/-	2, 3
	12	250	60	GP	6K				
	-	125-250	60	1/4hp	6K				
<b>ZYB</b>	16	250	60	GP	6K	65	2/1	PP/-	-
	-	125	60	3/4hp	6K				

\* - Temperature can either be 65C or 105C.

A1 - These switches, series R-MASK switches, may be provided with a rubber protection for dust when mounted on external flat surface of the end use equipment. The body and contacts have a temperature rating of 65°C or 100°C according to the suffix, C or H, instead the external button and gasket have a temperature rating of 50°C. The rubber was not evaluated as gasket use with water or other liquid.

Note 1 - In view of the use of steel current-carrying parts, the integrity of the lamp should be considered in the end-use.

Note 2 - The switches may be provided with terminals for printed circuit board connection. These terminals have not been investigated. The suitability of these terminals should be determined in the end-use application.

Note 3 - The F1 Series switches may control up to a total load of 20A with a maximum of 20A input on the common terminal and each pole (circuit) controlling up to its rated load.

Marking: Company name or trademark

MMOLVENO, catalog, model or part number, electrical ratings and the Recognized Component Mark, on the product or on the smallest unit container in which the product is packaged.

Last Updated on 2014-05-06

[Questions?](#)

[Print this page](#)

[Terms of Use](#)

[Page Top](#)

